



SPECIFICATIONS:

3.9" die cast trim (2.6" aperture) GE Constant Color® CMH MR16 metal halide fixed lamp downlight. with deep baffle reflector.

Trim Body

- Die cast aluminum trim body construction with external spring clips to secure trim body to rough-in. Internal spring clips secure reflector to trim body.

Reflector

- Spun aluminum deep regressed reflector with integral lamp and media holder secured by spring clip. Supports 1 media.
- Powder coat painted (white and black) and plated matte chrome finishes.

Trims

- 4" round or square trim shapes offered with powder coat painted (white, black, and metallic silver) and plated (chrome, polished gold, and satin nickel) finishes.
- Die cast aluminum construction with bayonet interlocking attachment to trim body.

Trim Accessories

- Interchangeable glass and decorative trim accessories interlock with either round or square trims for customized appearance.
- Protective, clear tempered glass supplied with fixture except when optional trim accessory is specified.

Electrical:

- Ceramic socket with pre-wired high temperature wire leads provided with rough-in housing. Rough-in ordered separately

Lamping:

- 20 watt, GE Constant Color® CMH MR 16 metal halide, GX10 TAL base. Ordered separately

Compliances:

- UL and cUL Listed when specified with appropriate A35 Series rough-in housing.
- Suitable for use in damp location or wet location for select trim accessories.

Ordering Information

To specify a complete catalog number, choose one item from the selection available in each module.

Example: M3.703MC – RWH – 00

Series	Lamping	Optic Style	Optic Finish	Trim Shape	Trim Finish	Trim Accessory
M3 .	7 – 20 watt GE Constant Color® CMH MR16	03 – deep baffle	WH – white BK - black MC – matte chrome	R – round S - square	WH - white BK - black MS – metallic silver CH - chrome GD – polished gold SN – satin nickel	00, 01, 02, 03, 04, 05, 06, 07, 08, 09, 10

Wet location available for the following trim accessories: 00, 01, 02, 03, 06, 07, 08, 09, 10. To order wet location option, add "W" after the trim accessory code, i.e. -03W.

Use with A35S-MH20MR-120 and A35R-MH20MR-120 Series rough-ins

Ardee Lighting reserves the right to change product specifications without prior notification.

Ardee Lighting		
PO Box 1769 · 639 Washburn Switch Rd · Shelby · NC 28151 T 704. 482.2811 F 800.275.1544 E ardee@jjishelby.com www.ardeelighting.com		
2/21/2007		222266